

Slideview 2

Dual MOT Slideshow viewer for Flashlog 7

The screenshot displays a dual MOT slideshow viewer interface. At the top, there are two dropdown menus: 'SKYsportsRadio1' on the left and 'WSFM ClassicHits' on the right. The main content is divided into two columns. The left column features a 'Next Race' section for 'Woodville Race 1' at 'YR1 10:50', with the 'SKY SPORTS RADIO' logo. Below this is a table of market orders with columns for 'MARKET ORDER', 'Win', and 'Plc'. The table lists five entries: 4. Ziphion (0.00, 0.00), 5. George Almighty (1.04, 42.00), 6. Surreal Storm (13.40, 1.00), 2. Bolt (12.90, 2.20), and 1. Settle Petal (50.30, 42.00). At the bottom of this section are 'TIPS' (6 5 3 2) and 'Late Mail:'. Below the table is a 'Last Race Results' section for 'Happy Valley Gallops R8', listing the top four finishers: 1st: #5-Tai Sing Yeh, 2nd: #1-Holey Dollar, 3rd: #11-Charmgold, and 4th: #4-Loyal Army. The right column features a 'NEWSROOM' section with the 'Classic Hits 101.7 WFSM' logo. It contains two news snippets: 'Opposition Leader BARRY O'FARRELL is warning motorists from Sydney's North West .. they'll pay Tens of thousands of ...' and 'A GOSFORD woman will face court in CANADA next month - charged with SECOND degree murder - over the death...'. At the bottom of the right column is the text 'Good Times, Great Classic Hits... 101.7 WFSM'.

MARKET ORDER	Win	Plc
4. Ziphion	0.00	0.00
5. George Almighty	1.04	42.00
6. Surreal Storm	13.40	1.00
2. Bolt	12.90	2.20
1. Settle Petal	50.30	42.00

Slideview 2 is a full-screen 32-bit Windows application showing the MOT slideshows and DLS text of two DAB+ services. It operates in conjunction with a Flashlog 7 logging recorder, connecting to it via an Ethernet network.

Slideview runs on Windows XP or later versions and requires a screen resolution of 1280 x 768 pixels. **Ensure that Windows display settings are configured correctly and that the monitor used is compatible with this mode.**

Install Slideview by running setup.exe from the distribution media. This will create a shortcut to the program in the Startup folder so it will automatically run whenever the PC is restarted.

When run for the first time, Slideview will display its Activation dialog.



Type in the network name of your Flashlog 7, as shown in the example above, then click on the Connect button. If a connection to the logger is established, a Hardware ID number will appear. Contact Innes Corporation and quote this number to receive your activation key which you must then enter before clicking on the Activate button. Note that activation is keyed to the Flashlog 7 hardware, so for any given logger, multiple PCs may run Slideview using the same activation key.

Alternatively, you may click on the Trial button, which will allow Slideview to run for a period of one week. While in trial mode, a button will be shown on the bottom of the screen to reopen the Activation dialog box. At the end of the trial period, Slideview will shut down and an activation key must then be entered in order to run it again.

Once Slideview is running, choose the services to monitor from the drop-down lists. If the lists are empty, it has been unable to connect to the logger, so make sure that both the logger and the Slideview PC have network connectivity.

Allow a little time for the slides and DLS text to appear. Complex slides can take several minutes to transmit.

To close the Slideview window, press Alt-F4 on the keyboard.